

TECNOLUMEN

TECNOLUMEN GmbH & Co. KG • Lötzeener Str. 2-4 • D-28207 Bremen • Tel (0421) 430 41 70 • Fax (0421) 4986685

Assembly instructions and important information HLWSP

Technical details:

Power supply: 110-240 V / 50-60 Hz

Bulb socket: E27

Protection class: I

Maximum wattage (thermal):

3 x 75 W

Recommended bulbs:

energy-saving bulb 15 W

Note:

This specified maximum wattage applies to conventional bulbs. Since these have however been off the market since 01.09.2009, we recommend energy-saving bulbs with about 1/5 of the specified wattage.

Halogen bulbs are not suitable because these become much hotter than conventional bulbs.

Safety instructions:

- This luminaire may only be wired to the mains by a qualified electrician.
Improper connection causes safety hazards!
- Always ensure that the electricity is switched off when working on the luminaire or changing the bulb.
- Have repair work performed only by an authorized electrician, because electrical power can cause severe injuries!
- Please note the specified maximum wattage of the bulbs.

**Fitting too strong a bulb may lead to discolouring
of the lampshade and fire hazard!**

Care of lamp:

Do not use a cleaning agent to clean the painted bulb device - only use a damp cloth.

Clean the upper side of the lampshade using a dry cloth and without exerting any pressure. The inside of the lampshade can be cleaning with a damp cloth.

Mounting the lampshade:

- At first lead the cable through the lampshade and then through the strain relief.
- Screw the strain relief on the threaded tube.
- Using the M5 screw, secure the strain relief at the threaded tube.
- Using the M6 screw of the strain relief, affix the cable. (Does not screw on too tight as this may damage the cable).

Please note the leaflet enclosed with the lampshade:

**“Important information on the
lampshades”**

Mounting the luminaire:

- Hang up the 3-hole hanger of the lamp on the ceiling hook provided by you.
- Have the electrical connection installed by an electrician as shown in the connection diagram.
- Affix the canopy over the terminals.

Layout and connection diagram:

