

TECNOLUMEN

TECNOLUMEN GmbH & Co. KG • Lötzeener Str. 2-4 • D-28207 Bremen • Tel (0421) 430 41 70 • Fax (0421) 4986685

Assembly instructions and important information WLZ 92 Africe

Technical details:

Power supply: 110-240 V / 50-60 Hz
EU: Dimmable electronic transformer:
USA: Transformers:
Maximum wattage (thermal):
Supplied bulb:

Bulb socket: GU4

Protection class: I
230-240 V / 12 V AC
110 V / 12 V AC
HAL 2 x 35 W
Halogen reflector bulb 12 V, Ø 35 mm, 35 W

Safety instructions:

- This luminaire may only be wired to the mains by a qualified electrician.
Improper connection causes safety hazards!
- Always ensure that the electricity is switched off when working on the luminaire or changing the bulb.
- Have repair work performed only by an authorized electrician, because electrical power can cause severe injuries!
- Some of the lamp components may get very hot in operation! Avoid skin contact with these components to prevent burns.

Care of lamp:

For cleaning the stainless steel lamp parts, aluminum parts and glass parts please use a rinsing agent or a glass cleaner.

Mounting the luminaire:

Lamp housing:

- Position the lamp at the desired place of installation. **The lamp must be in a vertical position!**
- Mark the drill holes on the wall with the aid of the drilling template and then drill the holes using an 8 mm (0.32 inch) masonry drill.
- Have the electrical connection installed by an electrician as shown in the connection diagram.
- Mount the lamp housing (A) to the wall using the screws and rawplugs supplied.

Lamp shade:

- After installing the lamp housing (A) on the wall, position loop (E) on catch cable over hook (C).
- Then slide the shade (B) onto housing with sleeve (D) on hook (C).
- Align the shade so that the light reflection on the wall symmetrical.

Assembly and connection diagram:

